



RF-2400D FM Radio

TUNER		Frequency Range	FM 87 - 108MHz (50kHz step) AM 520 - 1730kHz (9/10kHz step)
		AFC (Automatic Frequency Control)	yes
		Tuning	Digital
		Tuning LED	yes (Red)
AUDIO SYSTEM		Power Output (RMS)	770mW (MAX)
		AC Adaptor Mode	
		Battery Mode	
		DC In	
SPEAKER SYSTEM		Speaker Size	10 cm
TERMINAL		Earphone/ Headphone (3.5mm)	yes (mini/mono)
OTHERS	Power Source	Battery	DC 6V (R6/LR6, AA, UM-3) x 4
		AC	230 V, 50Hz
	Handle		yes
	Battery Life [Approx.]	Speaker	R6: FM 21 H, AM 20 H LR6: FM 52 H, AM 55 H
		Headphone	N/A, N/A
	Power Consumption (AC)		3W
DIMENSIONS, WEIGHT		Dimensions (W x H x D) [Approx.]	234 x 122 x 82 mm
		Weight (without batteries) [Approx.]	690 g
			•Specifications are subject to change without notice. Weight and dimensions are approximate.