



## RC-800 klockradio

Tuner	Band/Station Presets	FM(10)(87.50 ~ 108.00 MHz(50K step))	
	Auto Tuning	Yes	
	Radio Data System	-	
	Lead Antenna (FM)	Yes (1.0 m)	
Timer Function	Clock	Yes (Hr / Min (24h))	
	Alarm Timer	Yes (2 Alarm)	
	Kitchen Timer	-	
	Sleep Timer	Yes (120 / 90 / 60 / 30 minutes)	
	Rec Timer	-	
Function	Sound Source Setting	Yes for Alarm Timer (FM / BUZZER)	
	Setting start	Yes for Alarm Timer	
	Snooze	Yes	
	Battery	Battery Operation	-
		Battery Level Indication	-
Memory Backup Battery *1	Yes R6 / LR6 (AA Type) x 2pcs *2		
Sound Function	Preset EQ	-	
	Clear-mode dialog	-	
Bluetooth		-	
Amplifier	Amp Type	1ch AMP Analog	
	RMS Output Power	1W (8 Ohm, 1 kHz, 30%THD)	
Speaker System	Type	1 way, 1 speaker system (Closed Box)	

		Speaker Unit	Fullrange 5 cm Cone type x1
Terminal	Audio Out		-
	USB	Playback	-
		Type	-
		Battery Charge	-
Design	Display	Size (View area)	70 x 33.5 mm
		LED	Yes (Orange)
	10 stations preset tuning		Yes
	Front Net		Molding Net
General	Power Supply	AC-In / DC-In	DC-In (Fixed AC adaptor)
		Voltage	100-240V, 50/60Hz
	Fixed AC Adaptor		Yes (1.5m cord)
	Power Consumption	Normal Use [Approx.]	3W
		Standby [Approx.]	0.8W
	Dimmer		3 Step
Dimensions, Weight	Dimensions (W x H x D)		150 x 89 x 90 mm
	Weight	without battery	0.6 Kg (approximate)
		with battery *2	0.7 Kg (approximate)
Color			Black
Accessories			-
Note			<p>*1 The memory backup batteries retain the clock settings during power supply interruption. (These batteries do not power the unit.)</p> <p>*2 Battery is not included.</p> <p>Specifications are subject to change without notice. Weight and dimensions are approximate.</p>
TRADEMARK NOTICE:			The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Panasonic Corporation is under license. Other trademarks and trade names are those of their respective owners.

